












Feature operation

AutoDial		
Store	AutoDial 	AutoDial 
Use		AutoDial 
Display	Display 	AutoDial 

Call Forward		
Activate	Fwd 	
Deactivate		Fwd
Reinstate	Fwd 	Fwd
View number	Display 	Fwd

Call Pickup





		Pickup
--	-----------------------------------------------------------------------------------	--------

Call Waiting		
Answer		Call Waiting
	(Hold)	
Return to first call		
	(Goodbye)	

Conference

	Conf 	
--	----------------------------------------------------------------------------------------	-----------------------------------------------------------------------------------

Handsfree

Activate		
	(Handsfree)	(Goodbye) (to end the call)
Switch to handset		
Handset to handsfree		
	(Handsfree)	

Activate Headset

		
	(Headset)	(Goodbye) (to end the call)









Hold

Place a call on hold		
	(Hold)	
Return to a held call		
Last Number Redial		




Message

		
		(Msg/Inbox)













Ring Again

Activate	RngAgn 	
When notified		
Deactivate		RngAgn
Transfer	Trans 	
Adjust volume		or 
	(Volume +)	(Volume -)

Legend

Icon	Action
()	Indicates the key cap text label. For example, (Message).
	Lift the handset, press the line (DN) key or the Headset key.
	Replace the handset, or press  (Goodbye) to end the call.

Legend (continued)

Icon	Action
	Press a line/feature key.
	Dial a number.
	An icon flashes when a feature is being programmed. An icon lights steadily when a feature is active.
	Press the Services key once for Call Platform features, or press the Services key twice for local phone features.
	Press the Message/Inbox key.
	Press the Up/Down Navigation keys
	Press the Enter key
	Press the Headset key.
	Press the Handsfree key.
	Press the Mute (on/off) key.
	Press the Directory key.
	Press the Quit/Stop key.

Services and Telephone Options menus

Services menu		
		
(Services)		

Note: The **Services** menu contains the **Telephone Options**, **Password Admin**, **Virtual Office**, and **MG 1000B** menus. These options are not available on all Avaya 1120E IP Deskphones. Consult your system administrator.

The following are the most commonly used options:

Telephone Options menu

Volume adjustment

Pick one of:	
Ringer	
Handset Listen	
Handsfree Listen	
Headset Listen	
Buzzer	(Quit)

Contrast adjustment

		(Quit)
-------------------------------------------------------------------------------------	--------------------------------------------------------------------------------------	--------

Language

		(Quit)
-------------------------------------------------------------------------------------	--------------------------------------------------------------------------------------	--------

Note: This language setting controls the language used by features on your phone only. To set the language used elsewhere on your phone, press **Services** twice, select 1. Preferences, and select 2. Language.

Date/Time format

		(Quit)
-------------------------------------------------------------------------------------	--------------------------------------------------------------------------------------	--------

Local DialPad Tone

		(Quit)
-------------------------------------------------------------------------------------	--------------------------------------------------------------------------------------	--------

Ring type

	Play		(Quit)
-------------------------------------------------------------------------------------	------	---------------------------------------------------------------------------------------	--------

OnHook default path

		(Quit)
-------------------------------------------------------------------------------------	--------------------------------------------------------------------------------------	--------

Note: The **Directory** key provides access to Corporate Directory, Personal Directory, Redial List, and Callers List. For more information about your 1120E IP Deskphone, consult the *Avaya 1120E IP Deskphone User Guide* (NN43112-103).

Avaya 1120E IP Deskphone



*Note: If supported by your server, the data message waiting indicator provides a data alert. Contact your system administrator to find out if this feature is available for you.

AVAYA

Avaya 1120E IP Deskphone

For Avaya Communication Server 1000

Quick Reference Card



LEGAL NOTICE

While the information in this document is believed to be accurate and reliable, except as otherwise expressly agreed to in writing AVAYA PROVIDES THIS DOCUMENT "AS IS" WITHOUT WARRANTY OR CONDITION OF ANY KIND, EITHER EXPRESS OR IMPLIED. The information and/or products described in this document are subject to change without notice.

Date: November 2010
 Document Release: Standard 04.01
 Document Number: NN43112-106
 Copyright © 2010 Avaya Inc.
 All Rights Reserved.